

## Cisco Catalyst 3750-X and 3560-X Series Switches

The Cisco® Catalyst® 3750-X and 3560-X Series Switches are an enterprise-class lines of stackable and standalone switches, respectively. These switches provide high availability, scalability, security, energy efficiency, and ease of operation with innovative features such as Cisco StackPower, IEEE 802.3at Power over Ethernet Plus (PoE+) configurations, optional network modules, redundant power supplies, and Media Access Control Security (MACsec) features. The Cisco Catalyst 3750-X Series with StackWise® Plus technology provides scalability, ease of management and investment protection for the evolving business needs. The Cisco Catalyst 3750-X and 3560-X enhance productivity by enabling applications such as IP telephony, wireless, and video for borderless network experience.

Cisco Catalyst 3750-X and 3560-X Series primary features:

- 24 and 48 10/100/1000 PoE+ and non-PoE models
- Optional four Gigabit Ethernet (GbE) SFP or two 10GbE SFP+ uplink network modules
- Industry first PoE+ with 30W power on all ports in 1 rack unit (RU) form factor
- Dual redundant, modular power supplies and fans
- Media Access Control Security (MACsec) hardware-based encryption
- IPv4 and IPv6 routing, Multicast routing, advanced quality of service (QoS), and security features in hardware
- Enhanced limited lifetime warranty (LLW) with next business day (NBD) advance hardware replacement and 90 day access to Cisco Technical Assistance Center (TAC) support
- Enhanced Cisco EnergyWise for operational cost optimization by measuring actual power consumption of the PoE devices, reporting, and reducing energy consumption across the network
- USB Type-A and Type-B ports for storage and console respectively and an out-of-band Ethernet management port.

In addition to the above features, the Cisco Catalyst 3750-X switches also offer:

- Cisco StackPower™ technology: An innovative feature and industry first for sharing power among stack members
- Cisco StackWise Plus technology for ease of use and resiliency with 64 Gbps of throughput
- Investment protection with backward compatibility with all other models of Cisco Catalyst 3750 Series Switches

## Switch Configurations

All switch models can be configured with the optional four GbE or two 10 GbE network module. The switch models are available with either the LAN Base or IP Base feature set. IP Services feature set is available as an upgrade option at the time of ordering or through a license at a later time.

### Stackable Switches

Figure 1 shows the Cisco Catalyst 3750-X Series Switches (front and back).

**Figure 1.** Cisco Catalyst 3750-X Series Switches (Front and Back)



Table 1 shows the Cisco Catalyst 3750-X Series configurations.

**Table 1.** Cisco Catalyst 3750-X Series Configurations

Feature Set	Models	Total 10/100/1000 Ethernet Ports	Default AC Power Supply	Available PoE Power	StackPower
LAN Base	WS-C3750X-24T-L	24	350W	-	Available with upgrade to IP Base
	WS-C3750X-48T-L	48			
	WS-C3750X-24P-L	24 PoE+	715W	435W	
	WS-C3750X-48P-L	48 PoE+			
	WS-C3750X-48PF-L	48 PoE+			
IP Base	WS-C3750X-24T-S	24	350W	-	Yes
	WS-C3750X-48T-S	48			
	WS-C3750X-24P-S	24 PoE+	715W	435W	
	WS-C3750X-48P-S	48 PoE+			
	WS-C3750X-48PF-S	48 PoE+			

### Standalone Switches

Figure 2 shows Cisco Catalyst 3560-X Series Switches.

**Figure 2.** Cisco Catalyst 3560-X Series Switches



Table 2 shows the Cisco Catalyst 3560-X Series configurations.

**Table 2.** Cisco Catalyst 3560-X Series Configurations

Feature Set	Models	Total 10/100/1000 Ethernet Ports	Default AC Power Supply	Available PoE Power
LAN Base	WS-C3560X-24T-L	24	350W	–
	WS-C3560X-48T-L	48		
	WS-C3560X-24P-L	24 PoE+	715W	435W
	WS-C3560X-48P-L	48 PoE+		
	WS-C3560X-48PF-L	48 PoE+		
IP Base	WS-C3560X-24T-S	24	350W	–
	WS-C3560X-48T-S	48		
	WS-C3560X-24P-S	24 PoE+	715W	435W
	WS-C3560X-48P-S	48 PoE+		
	WS-C3560X-48PF-S	48 PoE+		
			1100W	800W

### Cisco Catalyst 3750-X and 3560-X Series Software

In addition to IP Base and IP Services feature sets, the Cisco Catalyst 3750-X and 3560-X Series come with a new LAN Base feature set. The three feature sets available with all Cisco Catalyst 3750-X and 3560-X Series Switches are:

- LAN Base: Enhanced Intelligent Services
- IP Base: Baseline Enterprise Services
- IP Services: Enterprise Services

The LAN Base feature set offers enhanced intelligent services that includes comprehensive Layer 2 features. The IP Base feature set provides baseline enterprise services in addition to all LAN Base features. IP Base also includes the support for routed access, StackPower, and MACsec. The IP Services feature set provides full enterprise services that includes advanced Layer 3 features such as Enhanced Interior Gateway Routing Protocol (EIGRP), Open Shortest Path First (OSPF), Border Gateway Protocol (BGP), Protocol Independent Multicast (PIM), and IPv6 routing such as OSPFv3 and EIGRPv6. IP Services feature set also includes the Embedded Event Manager (EEM) and IP service-level agreements (SLAs) initiator functionalities. All software feature sets support advanced security, QoS, and management features. The IP Services feature set is only available as an upgrade option at the time of ordering or through a license at a later time; there is no dedicated IP Services switch model.

The Cisco Catalyst 3750-X Series Switches with LAN Base feature set can only stack with other Cisco Catalyst 3750-X Series LAN Base switches. A mixed stack of LAN Base switch with IP Base or IP Services features set is not supported.

Customers can transparently upgrade the software feature set in the Cisco Catalyst 3750-X and 3560-X Series Switches through Cisco IOS<sup>®</sup> Software activation. Software activation authorizes and enables the Cisco IOS Software feature sets. A special file contained in the switch, called a license file, is examined by Cisco IOS Software when the switch is powered on. Based on the license's type, Cisco IOS Software activates the appropriate feature set. License types can be changed, or upgraded, to activate a different feature set. For detailed information about Software Activation, visit <http://www.cisco.com/go/sa>.

### Cisco StackWise Plus Technology

Cisco StackWise Plus technology is built on the highly successful industry leading StackWise technology, which is a premium stacking architecture optimized for GbE. StackWise technology was designed to respond to additions, deletions, and redeployment while maintaining constant performance. The stack behaves as a single switching unit that is managed by a master switch elected from one of the member switches. The master switch automatically

creates and updates all the switching and optional routing tables. A working stack can accept new members or delete old ones without service interruption. StackWise creates a highly resilient single unified system of up to nine switches, providing simplified management using a single IP address, single telnet session, single command-line interface (CLI), auto-version checking, autoconfiguration, and more. StackWise Plus supports all the features of StackWise and provides backward compatibility with the existing Cisco Catalyst 3750 Series Switches while enhancing the throughput of the system up to 64 Gbps. StackWise Plus also enables local switching in Cisco Catalyst 3750-X Series Switches. Local switching packets coming into a port in the Cisco Catalyst 3750-X Series or 3750-E Series Switch destined for another port in the same switch do not have to traverse through the stack ring, thus increasing the forwarding capacity of the switch. The Cisco Catalyst 3750-X Series stacks up to nine switches as a single logical unit for a total of 432 Ethernet 10/100/1000 ports with 18 10GbE ports. Individual 10/100/1000 units can be joined in any combination to evolve with network needs.

### Cisco StackPower Technology

The Cisco Catalyst 3750-X Series introduces Cisco StackPower technology, innovative power interconnect system that allows the power supplies in a stack to be shared as a common resource among all the switches. Cisco StackPower unifies the individual power supplies installed in the switches and creates a pool of power, directing that power where it is needed. This feature is only available in the Cisco Catalyst 3750-X Series Switches with IP Base or IP Services feature set. Up to four switches can be configured in a StackPower stack with the special connector at the back of the switch using the StackPower cable, which is different than the StackWise cables available on all Cisco Catalyst 3750 models. (See Figure 3.)

**Figure 3.** StackPower Connector



StackPower can be deployed in either power sharing mode or redundancy mode. In power sharing mode, the power of all the power supplies in the stack is aggregated and distributed among the switches in the stack. In redundant mode, when the total power budget of the stack is calculated, the wattage of the largest power supply is not included. That power is held in reserve and used to maintain power to switches and attached devices when one power supply fails, enabling the network to operate without interruption. Following the failure of one power supply, the StackPower mode becomes power sharing.

StackPower allows customers to simply add one extra power supply in any switch of the stack and provide either power redundancy for any of the stack members or simply add more power to the shared pool. StackPower eliminates the need for an external redundant power system or installation of dual power supplies in all the stack members.

## Network Module

Figure 4 shows network module with four GbE or two 10GbE SFP+ interfaces.

**Figure 4.** Network Module with Four GbE or Two 10GbE SFP+ Interfaces



The Cisco Catalyst 3750-X Series and 3560-X Series Switches support an optional network module for uplink ports. The default switch configuration doesn't include the uplink module; the customer has the flexibility to choose from four GbE port (3KX-NM-1G) or two 10GbE port (3KX-NM-10G) network module at the time of switch purchase. The 10GbE uplink module features four physical ports with two SFP+ and two regular SFP ports. The SFP+ interface supports both 10GbE and GbE port, allowing customer to use their investment in GbE SFP and upgrade to 10GbE when business demands change, without having to do a comprehensive upgrade of the access switch. The uplink module is hot swappable. The 10GbE network module can be used in any of the combinations shown in Table 3.

**Table 3.** 10GbE Network Module Configuration

10GbE Network Module	
10GbE SFP+ Ports	GbE SFP Ports
2	0
0	4
1	2

## MACsec

The Cisco Catalyst 3750-X and 3560-X Series Switches offer exceptional security with integrated hardware support for MACsec defined in IEEE 802.1AE. MACsec provides MAC layer encryption over wired networks using out-of-band methods for encryption keying. The MACsec Key Agreement (MKA) protocol provides the required session keys and manages the keys required for encryption when configured. MKA and MACsec are implemented following successful authentication using 802.1x Extensible Authentication Protocol (EAP) framework. In Cisco Catalyst 3750-X and 3560-X Series Switches only the user/down-link ports (links between the switch and endpoint devices such as a PC or IP phone) can be secured using MACsec.

## Dual Redundant Modular Power Supplies

The Cisco Catalyst 3750-X Series and 3560-X Series Switches support dual redundant power supplies. The switch ships with one power supply by default, and the second power supply can be purchased at the time of ordering the switch or at a later time. If only one power supply is installed, it should always be in the power supply bay 1.

**Figure 5.** Dual Redundant Power Supplies



Table 4 shows the different power supplies available in these switches and available PoE power.

**Table 4.** Power Supply Models

Models	Default Power Supply	Available PoE Power
24 Port Data Switch	C3KX-PWR-350WAC	–
48 Port Data Switch		
24 Port PoE Switch	C3KX-PWR-715WAC	435W
48 Port PoE Switch		
48 Port Full PoE Switch	C3KX-PWR-1100WAC	800W

In addition to the above power supplies a 440W DC power supply is available as a configurable option on all switch models. The DC power supply also delivers 175W of PoE for maximum flexibility, and customers can mix and match the AC and DC power supplies in the two available power supply slots. Any of these power supplies can be installed in any of the switches.

## Power over Ethernet Plus (PoE+)

In addition to PoE 802.3af, the Cisco Catalyst 3750-X and 3560-X Series Switches support PoE+ (IEEE 802.3at standard), which provides up to 30W of power per port. The Cisco Catalyst 3750-X and 3560-X Series Switches can provide a lower total cost of ownership for deployments that incorporate Cisco IP phones, Cisco Aironet® wireless LAN (WLAN) access points, or any IEEE 802.3af-compliant end device. PoE removes the need for wall power to each PoE-enabled device and eliminates the cost for additional electrical cabling and circuits that would otherwise be necessary in IP phone and WLAN deployments. Table 5 shows the power supply combinations required for different PoE needs.

**Table 5.** Power Supply Requirements for PoE and PoE+

	24 Port PoE Switch	48 Port PoE Switch
<b>PoE (15.4W per port)</b>	One C3KX-PWR-715WAC	One C3KX-PWR-1100WAC or Two C3KX-PWR-715WAC
<b>PoE+ (30W per port)</b>	One C3KX-PWR-1100WAC or Two C3KX-PWR-715WAC	Two C3KX-PWR-1100WAC or One C3KX-PWR-1100WAC and One C3KX-PWR-715WAC

### eXpandable Power System (XPS) 2200

The XPS 2200 (available at a later time frame) is the next-generation redundant power system (RPS). It not only provides the functionalities offered by the RPS but also provides enhanced services with the support for Cisco StackPower technology. When used with the Cisco Catalyst 3560-X, it provides RPS functionality, but when used with the Cisco Catalyst 3750-X, it provides StackPower+ functionality to all the stack members, including power supply redundancy.

The XPS supports dual redundant power supplies and fans. Up to nine switches can be connected to the XPS 2200, and it can provide power backup to two of the failed switches concurrently (when appropriately sized power supplies are used). The power supplies used the XPS 2200 are the same as the ones supported in the Cisco Catalyst 3750-X and 3560-X Series Switches. The XPS 2200 is fully configurable for setting switch priorities in case of multiple failures.

### Cisco Catalyst 3750-X and 3560-X Series Switches Enable Cisco Borderless Network Experience

Borderless Networks, a Cisco architecture, deliver the new workspace experience, connecting anyone, anywhere, using any device, to any resource securely, reliably, and transparently. Cisco's Borderless Networks architecture addresses primary IT and business challenges to help create a truly borderless experience by bringing interactions closer to the employee and customer.

Borderless experience is only possible with intelligent network elements designed and architected to meet the needs of a global workspace. Cisco Network Access is a primary component of this architecture, enabling various borderless network services such as mobility, security, MediaNet, EnergyWise, and ease of operations for increased productivity and operational efficiency. When network access is intelligent, it knows the identity of the user, as well as where the user is on the network. It knows what is connecting to the network, to automatically provision the network for QoS and delivery. It becomes services-aware to optimize user experience. Only with intelligent access network, your enterprise can go borderless securely and transparently. Your business can save energy, simplify operations with better business efficiency, and have an optimized total cost of ownership.

Cisco Network Access for Borderless solution focuses on the following primary areas:

- Sustainability
- Ease of operations
- Borderless security
- Borderless experience

### Sustainability

Cisco Catalyst switching solutions enable greener practices through measurable power efficiency, integrated services, and continuous innovations such as Cisco EnergyWise, an enterprisewide solution that monitors and conserves energy with customized policies. Together, Cisco EnergyWise technology and Cisco Catalyst switches

reduce greenhouse gas (GhG) emissions and increase energy cost savings and sustainable business behavior. Sustainability features in the Cisco Catalyst 3750-X and 3560-X Series Switches include the following features sets:

- Cisco EnergyWise technology
- Efficient switch operation
- Intelligent power management

### **Cisco EnergyWise Technology**

Cisco EnergyWise is an innovative architecture, added to fixed configuration switches, promoting companywide sustainability by reducing energy consumption across an entire corporate infrastructure and affecting more than 50 percent of global greenhouse gas emissions created by worldwide building infrastructure, a much greater effect than the 2 percent generated by the IT industry. Cisco EnergyWise enables companies to measure the power consumption of network infrastructure and network-attached devices and manage power consumption with specific policies, reducing power consumption to realize increased cost savings, potentially affecting any powered device.

EnergyWise encompasses a highly intelligent network-based approach to communicate messages that measure and control energy between network devices and endpoints. The network discovers Cisco EnergyWise manageable devices, monitors their power consumption, and takes action based on business rules to reduce power consumption. EnergyWise uses a unique domain-naming system to query and summarize information from large sets of devices, making it simpler than traditional network management capabilities. Cisco EnergyWise's management interfaces allow facilities and network management applications to communicate with endpoints and each other using the network as a unifying fabric. The management interface uses standard SNMP or TCP to integrate Cisco and third-party management systems.

### **Efficient Switch Operation**

Cisco Catalyst 3750-X and 3560-X Series Switches, designed and engineered by Cisco, provide optimum power saving, low power operations for industry best-in-class power management, and power consumption capabilities. The Cisco Catalyst 3750-X and 3560-X ports are capable of reduced power modes so that ports not in use can move into a lower power utilization state.

StackPower lets customers to simply add one extra power supply in any switch of the stack and provide either power redundancy for any of the stack members or simply add more power to the shared pool.

### **Intelligent Power over Ethernet Management**

The Cisco Catalyst 3750-X and 3560-X Series PoE models support Cisco IP phones and Cisco Aironet WLAN access points providing up to 30W of power per port, as well as any IEEE 802.3af-compliant end device.

- **Cisco Discovery Protocol Version 2** allows the Cisco Catalyst 3750-X and 3560-X Series Switches to negotiate a more granular power setting when connecting to a Cisco powered device such as IP phones or access points than what is provided by IEEE classification.
- **Per port power consumption** command allows customers to specify maximum power setting on an individual port.
- **Per port PoE power sensing** measures actual power being drawn, enabling more intelligent control of powered devices.
- **The PoE MIB** provides proactive visibility into power usage and allows customers to set different power-level thresholds.



## Ease of Operations

The Cisco Catalyst 3750-X and 3560-X help reduce the operating costs through:

- Cisco Catalyst Smart Operations
- Easy to use deployment and control features
- Advanced, intelligent network management tools

### Cisco Catalyst Smart Operations

Cisco Catalyst Smart Operations are a comprehensive set of capabilities that simplify LAN deployment, configuration, and troubleshooting. In addition to adaptive, always on technologies such as StackWise and StackPower, Cisco Catalyst Smart Operations enable zero touch installation and replacement of switches, fast upgrade, as well as ease of troubleshooting with reduced operational cost. **Cisco Catalyst Smart Operations** is a set of features that includes Smart Install, auto Smartports, Smart Configuration, and Smart Troubleshooting to enhance operational excellence:

- **Cisco Smart Install** is a transparent plug and play technology to configure the Cisco IOS Software image and switch configuration without user intervention. Smart Install utilizes dynamic IP address allocation and the assistance of other switches to facilitate installation providing transparent network plug and play.
- **Cisco Auto Smartports** provide automatic configuration as devices connect to the switch port, allowing auto detection and plug and play of the device onto the network.
- **Cisco Smart Configuration** provides a single point of management for a group of switches and in addition adds the ability to archive and backup configuration files to a file server or switch allowing seamless zero touch switch replacement.
- **Cisco Smart Troubleshooting** is an extensive array of debug diagnostic commands and system health checks within the switch, including Generic Online Diagnostics (GOLD) and Onboard Failure Logging (OBFL).

### Easy to Use Deployment and Control Features

- **Embedded Event Manager (EEM)** is a powerful and flexible feature that provides real-time network event detection and onboard automation. Using EEM, customers can adapt the behavior of their network devices to align with their business needs. This feature requires IP Services feature set.
- **IP service-level agreements (SLAs)** enable customers to assure new business-critical IP applications, as well as IP services that utilize data, voice, and video, in an IP network. This feature requires IP Services feature set.
- **Dynamic Host Configuration Protocol (DHCP)** autoconfiguration of multiple switches through a boot server eases switch deployment.
- **Automatic QoS (AutoQoS)** simplifies QoS configuration in voice over IP (VoIP) networks by issuing interface and global switch commands to detect Cisco IP phones, classify traffic, and help enable egress queue configuration.
- **Stacking master configuration management** and Cisco StackWise technology helps ensure that all switches are automatically upgraded when the master switch receives a new software version. Automatic software version checking and updating help ensure that all stack members have the same software version.
- **Autonegotiation** on all ports automatically selects half- or full-duplex transmission mode to optimize bandwidth.
- **Dynamic Trunking Protocol (DTP)** facilitates dynamic trunk configuration across all switch ports.
- **Port Aggregation Protocol (PAgP)** automates the creation of Cisco Fast EtherChannel<sup>®</sup> groups or Gigabit EtherChannel groups to link to another switch, router, or server.

- **Link Aggregation Control Protocol (LACP)** allows the creation of Ethernet channeling with devices that conform to IEEE 802.3ad. This feature is similar to Cisco EtherChannel technology and PAGP.
- **Automatic media-dependent interface crossover (MDIX)** automatically adjusts transmit and receive pairs if an incorrect cable type (crossover or straight-through) is installed.
- **Unidirectional Link Detection Protocol (UDLD)** and Aggressive UDLD allow unidirectional links caused by incorrect fiber-optic wiring or port faults to be detected and disabled on fiber-optic interfaces.
- **Switching Database Manager (SDM)** templates for access, routing, and VLAN deployment allow the administrator to easily maximize memory allocation to the desired features based on deployment-specific requirements.
- **Local Proxy Address Resolution Protocol (ARP)** works in conjunction with Private VLAN Edge to minimize broadcasts and maximize available bandwidth.
- **VLAN1 minimization** allows VLAN1 to be disabled on any individual VLAN trunk.
- **Smart Multicast, with Cisco StackWise Plus technology**, allows the Cisco Catalyst 3750-X Series to offer greater efficiency and support for more multicast data streams such as video by putting each data packet onto the backplane only once.
- **Internet Group Management Protocol (IGMP) Snooping** for IPv4 and IPv6 MLD v1 and v2 Snooping provide fast client joins and leaves of multicast streams and limit bandwidth-intensive video traffic to only the requestors.
- **Multicast VLAN Registration (MVR)** continuously sends multicast streams in a multicast VLAN while isolating the streams from subscriber VLANs for bandwidth and security reasons.
- **Per-port broadcast, multicast, and unicast storm control** prevents faulty end stations from degrading overall systems performance.
- **Voice VLAN** simplifies telephony installations by keeping voice traffic on a separate VLAN for easier administration and troubleshooting.
- **Cisco VLAN Trunking Protocol (VTP)** supports dynamic VLANs and dynamic trunk configuration across all switches.
- **Remote Switch Port Analyzer (RSPAN)** allows administrators to remotely monitor ports in a Layer 2 switch network from any other switch in the same network.
- For enhanced traffic management, monitoring, and analysis, the Embedded **Remote Monitoring (RMON)** software agent supports four RMON groups (history, statistics, alarms, and events).
- **Layer 2 traceroute** eases troubleshooting by identifying the physical path that a packet takes from source to destination.
- **Trivial File Transfer Protocol (TFTP)** reduces the cost of administering software upgrades by downloading from a centralized location.
- **Network Timing Protocol (NTP)** provides an accurate and consistent timestamp to all intranet switches.

### Advanced, Intelligent Network Management Tools

The Cisco Catalyst 3750-X and 3560-X Series Switches offer both a superior CLI for detailed configuration and Cisco Network Assistant software, a PC-based tool for quick configuration based on preset templates. In addition, CiscoWorks LAN Management Solution (LMS) supports the Cisco Catalyst 3750-X and 3560-X Series Switches for networkwide management.

## Cisco Network Assistant

A PC-based network management application designed for small and medium-sized business (SMB) networks with up to 250 users, Cisco Network Assistant offers centralized network management and configuration capabilities. Cisco Network Assistant uses Cisco Smartports technology to simplify both initial deployment and ongoing maintenance. This application also features an intuitive GUI where users can easily apply common services across Cisco switches, routers, and access points, such as:

- Configuration management
- Troubleshooting advice
- Inventory reports
- Event notification
- Network security settings
- Password synchronization
- Drag-and-drop Cisco IOS Software upgrades
- Secure wireless

For detailed information about Cisco Network Assistant, visit <http://www.cisco.com/go/cna>.

## CiscoWorks LAN Management Solution

CiscoWorks LAN Management Solution (LMS) is a comprehensive network lifecycle management solution. It provides an extensive library of easy-to-use features to automate the initial and day-to-day management of your Cisco network infrastructure. CiscoWorks LMS uniquely uses Cisco hardware and software platform knowledge and operational experience into a powerful set of work-flow driven configuration, monitoring, troubleshooting, reporting, and administrative tools. Including:

- Support for new Cisco hardware platforms the day they ship
- Support for new technologies and services from initial deployment to day-to-day administration and management, such as EnergyWise, Identity, Cisco Auto Smartports, Cisco Smart Install, and much more
- Configuration management tools built from Cisco experience and Cisco Validated Design recommendations
- Monitoring and troubleshooting capabilities that incorporates Cisco hardware best practices and diagnostics features
- Automation in managing hardware inventories, security vulnerabilities (PSIRTS) and platform end-of-life and support cycles

For detailed information about CiscoWorks LMS, go to <http://www.cisco.com/en/US/products/sw/cscowork/ps2425/index.html>.

## Borderless Security

The Cisco Catalyst 3750-X and 3560-X Series Switches provide superior Layer 2 threat defense capabilities for mitigating man-in-the-middle attacks (such as MAC, IP, and ARP spoofing). TrustSec, a primary element of Borderless Security Architecture, helps enterprise customers secure their networks, data and resources with policy-based access control, identity and role-aware networking, pervasive integrity, and confidentiality. The borderless security is enabled by the following feature sets in the Cisco Catalyst 3750-X and 3560-X Series Switches:

- Threat defense
- Cisco TrustSec
- Other advanced security features

## Threat Defense

Cisco Integrated Security Features is an industry-leading solution available on Cisco Catalyst Switches that proactively protects your critical network infrastructure. Delivering powerful, easy-to-use tools to effectively prevent the most common and potentially damaging Layer 2 security threats, Cisco Integrated Security Features provides robust security throughout the network. Cisco Integrated Security Features include Port Security, DHCP Snooping, Dynamic ARP Inspection, and IP Source guard.

- **Port Security** secures the access to an access or trunk port based on MAC address. It limits the number of learned MAC addresses to deny MAC address-flooding.
- **DHCP Snooping** prevents malicious users from spoofing a DHCP server and sending out bogus addresses. This feature is used by other primary security features to prevent a number of other attacks such as ARP poisoning.
- **Dynamic ARP Inspection (DAI)** helps ensure user integrity by preventing malicious users from exploiting the insecure nature of the ARP protocol.
- **IP source guard** prevents a malicious user from spoofing or taking over another user's IP address by creating a binding table between the client's IP and MAC address, port, and VLAN.

## Cisco TrustSec

TrustSec secures access to the network, enforces security policies, and delivers standard based security solutions such as 802.1X enabling secure collaboration and policy compliance. TrustSec capabilities reflect Cisco thought leadership, innovations, and commitment to customer success. These new capabilities include:

- **IEEE 802.1AE MACsec** with prestandard 802.1X-REV Key management: industry's first fixed switches with prestandard 802.1X-Rev key management. Available on Cisco Catalyst 3750-X and 3560-X Series Switches, MACsec provides Layer 2, line rate Ethernet data confidentiality and integrity on host facing ports, protecting against man-in-the-middle attacks (snooping, tampering, and replay).
- **Flexible authentication** that supports multiple authentication mechanisms including 802.1X, MAC Authentication Bypass and web authentication using a single, consistent configuration.
- **Open mode** that creates a user friendly environment for 802.1X operations.
- **Integration of device profiling technology and guest access** handling with Cisco switching to significantly improve security while reducing deployment and operational challenges.
- **RADIUS Change of Authorization and downloadable Calls** for Comprehensive policy management capabilities.
- **802.1X Supplicant with Network Edge Access Transport (NEAT)** enables extended secure access where compact switches in the conference rooms have the same level of security as switches inside the locked wiring closet.

## Other Advanced Security Features

Other Advanced Security features include but are not limited to:

- **Private VLANs** restrict traffic between hosts in a common segment by segregating traffic at Layer 2, turning a broadcast segment into a nonbroadcast multiaccesslike segment.
- **Private VLAN Edge** provides security and isolation between switch ports, which helps ensure that users cannot snoop on other users' traffic.
- **Unicast Reverse Path Forwarding (RPF)** feature helps mitigate problems caused by the introduction of malformed or forged (spoofed) IP source addresses into a network by discarding IP packets that lack a verifiable IP source address.

- **Multidomain Authentication** allows an IP phone and a PC to authenticate on the same switch port while placing them on appropriate voice and data VLAN.
- **Cisco security VLAN ACLs** on all VLANs prevent unauthorized data flows from being bridged within VLANs.
- **Cisco standard and extended IP security router ACLs** define security policies on routed interfaces for control-plane and data-plane traffic. IPv6 ACLs can be applied to filter IPv6 traffic.
- **Port-based ACLs** for Layer 2 interfaces allow security policies to be applied on individual switch ports.
- **Secure Shell (SSH) Protocol, Kerberos, and Simple Network Management Protocol Version 3 (SNMPv3)** provide network security by encrypting administrator traffic during Telnet and SNMP sessions. SSH Protocol, Kerberos, and the cryptographic version of SNMPv3 require a special cryptographic software image because of U.S. export restrictions.
- Bidirectional data support on the **Switched Port Analyzer (SPAN)** port allows Cisco Intrusion Detection System (IDS) to take action when an intruder is detected.
- **TACACS+ and RADIUS authentication** facilitates centralized control of the switch and restricts unauthorized users from altering the configuration.
- **MAC Address Notification** allows administrators to be notified of users added to or removed from the network.
- **Multilevel security on console access** prevents unauthorized users from altering the switch configuration.
- **Bridge protocol data unit (BPDU) Guard** shuts down Spanning Tree PortFast-enabled interfaces when BPDUs are received to avoid accidental topology loops.
- **Spanning Tree Root Guard (STRG)** prevents edge devices not in the network administrator's control from becoming Spanning Tree Protocol root nodes.
- **IGMP filtering** provides multicast authentication by filtering out nonsubscribers and limits the number of concurrent multicast streams available per port.
- **Dynamic VLAN assignment** is supported through implementation of VLAN Membership Policy Server client capability to provide flexibility in assigning ports to VLANs. Dynamic VLAN facilitates the fast assignment of IP addresses.

### Borderless Experience

Borderless network enables enterprise mobility and business-grade video services. Industry's first unified network (wired and wireless) location services enable tracking of mobile assets and the users of those assets for both wired and wireless devices. The true borderless experience is enabled by the following feature sets in the Cisco Catalyst 3750-X and 3560-X Series Switches:

- High availability
- High-performance IP routing
- Superior QoS
- Location awareness and mobility

### High Availability

The Cisco Catalyst 3750-X Series increases availability for stackable switches. Each switch can operate both as master controller and as forwarding processor. Each switch in the stack can serve as a master, creating a 1:N availability scheme for network control. In the unlikely event of a single unit failure, all other units continue to forward traffic and maintain operation.

Other high-availability features include but are not limited to:

- Cross-Stack EtherChannel provides the ability to configure Cisco EtherChannel technology across different members of the stack for high resiliency.
- Flexlink provides link redundancy with convergence time less than 100 ms.
- IEEE 802.1s/w Rapid Spanning Tree Protocol (RSTP) and Multiple Spanning Tree Protocol (MSTP) provide rapid spanning-tree convergence independent of spanning-tree timers and also offers the benefit of Layer 2 load balancing and distributed processing. Stacked units behave as a single spanning-tree node.
- Per-VLAN Rapid Spanning Tree (PVRST+) allows rapid spanning-tree reconvergence on a per-VLAN spanning-tree basis, without requiring the implementation of spanning-tree instances.
- Cisco Hot Standby Router Protocol (HSRP) is supported to create redundant, failsafe routing topologies.
- Switch-port autorecovery (Errdisable) automatically attempts to reactivate a link that is disabled because of a network error.

### High-Performance IP Routing

Cisco Express Forwarding hardware routing architecture delivers extremely high-performance IP routing in the Cisco Catalyst 3750-X and 3560-X Series Switches.

- IP unicast routing protocols (Static, Routing Information Protocol Version 1 [RIPv1], and RIPv2, RIPv6, EIGRP stub) are supported for small-network routing applications with IP Base feature set.
- Advanced IP unicast routing protocols (OSPF, EIGRP, BGPv4, and IS-ISv4) are supported for load balancing and constructing scalable LANs. IPv6 routing (OSPFv3, EIGRPv6) is supported in hardware for maximum performance. The IP Services feature set is required.
- Equal-cost routing facilitates Layer 3 load balancing and redundancy across the stack.
- Policy-based routing (PBR) allows superior control by facilitating flow redirection regardless of the routing protocol configured. The IP Services feature set is required.
- Hot Standby Routing Protocol (HSRP) provides dynamic load balancing and failover for routed links, up to 32 HSRP links supported per unit or stack.
- Protocol Independent Multicast (PIM) for IP multicast routing is supported, including PIM sparse mode (PIM-SM), PIM dense mode (PIM-DM), PIM sparse-dense mode and Source Specific Multicast (SSM). The IP Services feature set is required.
- Virtual routing and forwarding (VRF)-Lite enables a service provider to support two or more VPNs, with overlapping IP addresses. IP Services feature set is required.

### Superior Quality of Service

The Cisco Catalyst 3750-X and 3560-X Series offers GbE speed with intelligent services that keep everything flowing smoothly, even at 10 times the normal network speed. Industry-leading mechanisms for marking, classification, and scheduling deliver superior performance for data, voice, and video traffic, all at wire speed.

Following are some of the QoS features supported in the Cisco Catalyst 3750-X and 3560-X Series Switches:

- Cross-stack QoS allows QoS to be configured across the entire stack.
- 802.1p class of service (CoS) and differentiated services code point (DSCP) field classification are provided, using marking and reclassification on a per-packet basis by source and destination IP address, MAC address, or Layer 4 TCP/UDP port number.
- Cisco control-plane and data-plane QoS ACLs on all ports help ensure proper marking on a per-packet basis.
- Eight egress queues per port help enable differentiated management of different traffic types across the stack. Four queues are user configurable and four are reserved for system use.

- Shaped Round Robin (SRR) scheduling helps ensure differential prioritization of packet flows by intelligently servicing the ingress queues and egress queues.
- Weighted Tail Drop (WTD) provides congestion avoidance at the ingress and egress queues before a disruption occurs.
- Strict priority queuing helps ensure that the highest-priority packets are serviced ahead of all other traffic.
- The Cisco committed information rate (CIR) function provides bandwidth in increments as low as 8 Kbps.
- Rate limiting is provided based on source and destination IP address, source and destination MAC address, Layer 4 TCP/UDP information, or any combination of these fields, using QoS ACLs (IP ACLs or MAC ACLs), class maps, and policy maps.
- Up to 64 aggregate or individual policers are available per Fast Ethernet or GbE port.

### **Location Awareness and Mobility**

In order to provide delivery of a best-in-class network experience to end users, it's critical for network access to be location aware. A wide variety of devices can appear on the network, both wired (switches, routers, IP phones, PCs, access points, controllers, video digital media players, and so on) and wireless (mobile devices, wireless tags, rogues, and so on). In many industries, locating assets is primarily a manual process and is time consuming and error prone. The inability to locate assets in real time and to help ensure their availability when and where they are needed limits reaction time and efficiency.

Location services answer business-critical questions about both mobile assets and the users of those assets regardless of whether those assets are connecting using wired or wireless, and hence directly improve their organization's profitability. Network Location Services also improve security and accelerate client troubleshooting by locating an asset, user, or device on the network.

- Network visibility and control provide centralized visibility into wired and wireless devices on the network and their location.
- Location-assisted client troubleshooting enables tracking of wired or wireless clients for quick problem resolution.
- Asset tracking and improved security provide centralized inventory of wired and wireless devices and asset management for improved business processes.
- Cisco Mobility Service Engine (MSE) Open API provides an open API (based on Simple Object Access Protocol [SOAP] and XML protocol) for any business application that needs the location data.
- Location based policy allows greater control and visibility. With EnergyWise, power policies can be set up (to reduce the power or shut down the power from a port) based on the location.
- Cisco Emergency Responder (CER) enhances emergency calling from Cisco Unified CallManager. It helps assure that Cisco Unified CallManager sends emergency calls to the appropriate Public Safety Answering Point (PSAP) for the caller's location.

## Cisco Catalyst 3750-X and 3560-X Series Specifications

### Switch Performance

Table 6 shows Cisco Catalyst 3750-X and 3560-X Series Switches performance specifications.

**Table 6.** Cisco Catalyst 3750-X and 3560-X Performance Specifications

Performance Numbers for All Switch Models	
Switching Fabric	160 Gbps
DRAM	256 MB
Flash	128 MB
Total VLANs	1005
VLAN IDs	4K
Total Switched Virtual Interfaces (SVIs)	1K
Jumbo Frame	9216 Byte
Total Routed Ports per 3750-X Stack	468
Forwarding Rate of the Switch Models (with Two 10GbE Uplinks)	
	Forwarding Rate
3750X-24T	65.5 mpps
3750X-24P	
3750X-48T	101.2 mpps
3750X-48P	
3750X-48PF	
3560X-24T	65.5 mpps
3560X-24P	
3560X-48T	101.2 mpps
3560X-48P	
3560X-48PF	

### Scalability Numbers

MAC, routing, security, and QoS scalability numbers depend on the type template used in the switch. Routing template is not supported in the LAN Base feature set. Table 7 shows Cisco Catalyst 3750-X and 3560-X Series Switch scalability numbers.

**Table 7.** Cisco Catalyst 3750-X and 3560-X Series Switch Scalability Numbers

	Access	Default	Routing	VLAN
<b>Unicast MAC addresses</b>	4K	6K	3K	12K
<b>IGMP groups and multicast routes</b>	1K	1K	1K	1K
<b>Unicast routes</b>	6K	8K	11K	0
<b>Directly connected hosts</b>	4K	6K	3K	0
<b>Indirect routes</b>	2K	2K	8K	0
<b>Policy-based routing ACEs</b>	0.5K	0	0.5K	0
<b>QoS classification ACEs</b>	0.5K	0.5K	0.5K	0.5K
<b>Security ACEs</b>	2K	1K	1K	1K
<b>VLANs</b>	1K	1K	1K	1K



## Dimensions, Weight, Acoustic, MTBF, and Environmental Range Specifications for Cisco Catalyst 3750-X and 3560-X Series Switches

Table 8 shows dimensions, weight, acoustic, MTBF, and environmental range.

**Table 8.** Dimensions, Weight, Acoustic, MTBF, and Environmental Range

Dimensions (H x W x D)	Inches	Centimeters
3750X-24T	1.75 x 17.5 x 18.0	4.45 x 44.5 x 46.0
3750X-24P		
3750X-48T		
3750X-48P		
3750X-48PF	1.75 x 17.5 x 19.5	4.45 x 44.5 x 49.5
3560X-24T	1.75 x 17.5 x 18.0	4.45 x 44.5 x 46.0
3560X-24P		
3560X-48T		
3560X-48P		
3560X-48PF	1.75 x 17.5 x 19.5	4.45 x 44.5 x 49.5
Weight	Pounds	Kilograms
3750X-24T	15.6	7.1
3750X-24P	15.8	7.2
3750X-48T	16.3	7.4
3750X-48P	16.5	7.5
3750X-48PF	16.7	7.6
3560X-24T	15.4	7.0
3560X-24P	15.7	7.1
3560X-48T	16.1	7.3
3560X-48P	16.4	7.4
3560X-48PF	16.6	7.5
Mean Time Between Failure (MTBF) Hours		
3750X-24T	189,704	
3750X-24P	167,198	
3750X-48T	171,846	
3750X-48P	139,913	
3750X-48PF	139,913	
3560X-24T	208,218	
3560X-24P	181,370	
3560X-48T	186,778	
3560X-48P	149,594	
3560X-48PF	149,594	
C3KX-PWR-350WAC	580,710	
C3KX-PWR-715WAC	664,055	
C3KX-PWR-1100WAC	392,174	
C3KX-PWR-440WDC	469,350	
C3KX-NM-1G	5,083,574	
C3KX-NM-10G	2,468,553	

Environmental Ranges	
<b>With AC Power Supply</b>  <b>Operating Environment and Altitude</b>	Normal Operating Temperature and Altitudes: -5°C to +45°C, up to 5,000 feet (1500 m) -5°C to +40°C, up to 10,000 feet (3000 m)
	Short-Term* Exceptional Conditions: -5°C to +50°C, up to 5,000 feet (1500 m) -5°C to +45°C, up to 10,000 feet (3000 m) -5°C to +45°C, at sea level with single fan failure * Not more than following in one year period: 96 consecutive hours, or 360 hours total, or 15 occurrences
<b>With DC Power Supply</b>  <b>Operating Environment and Altitude</b>	Normal Operating Temperature and Altitudes: -5°C to +45°C, up to 6,000 feet (1800 m) -5°C to +40°C, up to 10,000 feet (3000 m) -5°C to +35°C, up to 13,000 feet (4000 m)
	Short-Term* Exceptional Conditions: -5°C to +55°C, up to 5,000 feet (1800 m) -5°C to +50°C, up to 10,000 feet (3000 m) -5°C to +45°C, up to 10,000 feet (4000 m) -5°C to +45°C, at sea level with single fan failure * Not more than following in one year period: 96 consecutive hours, or 360 hours total, or 15 occurrences
<b>Acoustic Noise</b> (with 16 PoE+ ports loaded)	With AC Power Supply: LpA: 43 dbA Typical, 46 dbA Maximum LwA: 5.2 Bel Typical, 5.5 Bel Maximum  With DC Power Supply: LpA: 44 dbA Typical, 47 dbA Maximum LwA: 5.3 Bel Typical, 5.6 Bel Maximum
<b>Relative Humidity</b>	5% to 95%, non-condensing
<b>Storage Environment:</b>	Temperature: -40 C' to 70 C' Altitude: 15,000 ft
<b>Vibration</b>	Operating: 0.41Grms from 3 to 500Hz with spectral break points of 0.0005 G2/Hz at 10Hz and 200Hz 5dB/octave roll off at each end.
	Non-Operating: 1.12Grms from 3 to 500Hz with spectral break points of 0.0065 G2/Hz at 10Hz and 100Hz 5dB/octave roll off at each end.
<b>Shock</b>	Operating: 30G, 2ms Half sine
	Non-Operating: 55G, 10ms Trapezoid

### Connectors and LED Indicators for Cisco Catalyst 3750-X and 3560X Series

Table 9 shows connectors and LED indicators.

**Table 9.** Connectors and LED Indicators

<b>Connectors and Cabling</b>	<ul style="list-style-type: none"> <li>• 1000BASE-T ports: RJ-45 connectors, 2-pair Cat-5E UTP cabling</li> <li>• 1000BASE-T SFP-based ports: RJ-45 connectors, 2-pair Cat-5E UTP cabling</li> <li>• 100BASE-FX, 1000BASE-SX, -LX/LH, -ZX, -BX10, DWDM and CWDM SFP Transceivers: LC fiber connectors (single-mode or multimode fiber)</li> <li>• 10GBASE-SR, LR, LRM, CX1 (v02 or higher) SFP+ Transceivers: LC fiber connectors (single-mode or multimode fiber)</li> <li>• Cisco StackWise stacking ports: copper-based Cisco StackWise cabling</li> <li>• Cisco StackPower: Cisco Proprietary Power Stacking cables</li> <li>• Ethernet Management port: RJ-45 connectors, 2-pair Cat-5 UTP cabling</li> <li>• Management console port: RJ-45-to-DB9 cable for PC connections</li> </ul>
<b>Power Connectors</b>	<ul style="list-style-type: none"> <li>• Customers can provide power to a switch by using either the internal power supply or the Cisco XPS 2200. The connectors are located at the back of the switch.</li> <li>• Internal power supply connector: The internal power supply is an autoranging unit. The internal power supply supports input voltages between 100 and 240VAC. Use the supplied AC power cord to connect the AC power connector to an AC power outlet.</li> </ul>

## Management and Standards Support for Cisco Catalyst 3750-X and 3560-X Series Switches

Table 10 shows management and standards support for the Cisco Catalyst 3750-X and 3560-X Series.

**Table 10.** Management and Standards Support for the Cisco Catalyst 3750-X and 3560-X Series

Description	Specification	
<b>Management</b>	BRIDGE-MIB CISCO-CDP-MIB CISCO-CLUSTER-MIB CISCO-CONFIG-MAN-MIB CISCO-ENTITY-FRU-CONTROL-MIB CISCO-ENVMON-MIB CISCO-FLASH-MIB CISCO-FTP-CLIENT-MIB CISCO-HSRP-MIB CISCO-HSRP-EXT-MIB CISCO-IGMP-FILTER-MIB CISCO-IMAGE-MIB CISCO-IP-STAT-MIB CISCO-L2L3-INTERFACE-CONFIG-MIB CISCO-POE-EXTENSIONS-MIB CISCO-MAC-NOTIFICATION-MIB CISCO-MEMORY-POOL-MIB CISCO-PAGP-MIB CISCO-PING-MIB CISCO-PROCESS-MIB CISCO-RTTMON-MIB CISCO-STP-EXTENSIONS-MIB CISCO-SYSLOG-MIB CISCO-TCP-MIB CISCO-VLAN-IFTABLE-RELATIONSHIP-MIB CISCO-VLAN-MEMBERSHIP-MIB	CISCO-VTP-MIB ENTITY-MIB ETHERLIKE-MIB IF-MIB IGMP-MIB IPMROUTE-MIB OLD-CISCO-CHASSIS-MIB OLD-CISCO-FLASH-MIB OLD-CISCO-INTERFACES-MIB OLD-CISCO-IP-MIB OLD-CISCO-SYS-MIB OLD-CISCO-TCP-MIB OLD-CISCO-TS-MIB OSPF-MIB (RFC 1253) PIM-MIB RFC1213-MIB RFC1253-MIB RMON-MIB RMON2-MIB SNMP-FRAMEWORK-MIB SNMP-MPD-MIB SNMP-NOTIFICATION-MIB SNMP-TARGET-MIB SNMPv2-MIB TCP-MIB UDP-MIB
<b>Standards</b>	IEEE 802.1s IEEE 802.1w IEEE 802.1x IEEE 802.1x-Rev IEEE 802.3ad IEEE 802.1ae IEEE 802.3af IEEE 802.3at IEEE 802.3x full duplex on 10BASE-T, 100BASE-TX, and 1000BASE-T ports IEEE 802.1D Spanning Tree Protocol IEEE 802.1p CoS Prioritization IEEE 802.1Q VLAN IEEE 802.3 10BASE-T specification IEEE 802.3u 100BASE-TX specification IEEE 802.3ab 1000BASE-T specification IEEE 802.3z 1000BASE-X specification	RMON I and II standards SNMPv1, SNMPv2c, and SNMPv3

## Power Supply Specifications

Table 11 lists the power specifications for the Cisco Catalyst 3750-X and 3560-X Series based on the kind of power supply used.

**Table 11.** Power Specifications for Cisco Catalyst 3750-X and 3560-X Series

Description	Specification			
	C3KX-PWR-1100WAC	C3KX-PWR-715WAC	C3KX-PWR-350WAC	C3KX-PWR-440WDC
<b>Power Supply Rated Maximum</b>	1100W	750W	265W	265W
<b>Total Output BTU (Note: 1000 BTU/hr = 293W)</b>	3793 BTU/hr, 1100W	2465 BTU/hr, 715W	1207BTU/hr, 350W	1517BTU/hr, 440W
<b>Input-Voltage Range and Frequency</b>	115–240VAC, 50–60 Hz	100–240VAC, 50–60 Hz	100–240VAC, 50–60 Hz	-36VDC to -72VDC
<b>Input Current</b>	12–6A	10–5A	4–2A	<8A@-72VDC <16A@-36VDC
<b>Output Ratings</b>	-56V@19.64A	-56V@12.8A	-56V@6.25A	-56V@7.86A
<b>Output Holdup Time</b>	10 ms minimum @ 102.5VAC	16.7 ms minimum @ 100VAC	16.7 ms minimum @ 100VAC	> 2ms@-48VDC
<b>Power-Supply Input Receptacles</b>	IEC 320-C16 (IEC60320-C16)	IEC 320-C16 (IEC60320-C16)	IEC 320-C14 (IEC60320-C14)	Terminal Strip
<b>Power Cord Rating</b>	15A	15A	10A	20A @ 100VDC
<b>Physical Specifications</b>	(H x W x D): 1.58 X 3.25 X 13.25 in Weight: 3.5 lb (1.6 kg)	(H x W x D): 1.58 X 3.25 X 11.75 in Weight: 2.78 lb (1.26 kg)	(H x W x D): 1.58 X 3.25 X 11.75 in Weight: 2.76 lb (1.25 kg)	(H x W x D): 1.58 X 3.25 X 11.75 in Weight: 2.65 lb (1.2 kg)
<b>Operating Temperature</b>	23 to 113°F (-5 to 45°C)			
<b>Storage Temperature</b>	-40 to 158°F (-40 to 70°C)			
<b>Relative Humidity Operating, and Nonoperating Noncondensing</b>	5 to 90% noncondensing			
<b>Altitude</b>	10,000 ft. (3000 meters), up to 45°C			
<b>MTBF</b>	Calculated MTBF must be greater than 300,000 using Telcordia SR-332, Method 1, Case 3. Demonstrated MTBF is 500,000 hr (with 90% confidence level).			
<b>EMI and EMC Compliance</b>	FCC Part 15 (CFR 47) Class A ICES-003 Class A EN 55022 Class A CISPR 22 Class A AS/NZS 3548 Class A BSMI Class A (AC input models only) VCCI Class A EN 55024, EN300386, EN 50082-1, EN 61000-3-2, EN 61000-3-3 EN61000-4-2, EN61000-4-3, EN61000-4-4, EN61000-4-5, EN61000-4-6, EN 61000-6-1			
<b>Safety Compliance</b>	UL 60950-1, CAN/CSA-C22.2 No. 60950-1, EN 60950-1, IEC 60950-1, CCC			
<b>LED Indicators</b>	"AC OK": Input power to the power supply is OK. "PS OK": Output power from the power supply is OK.			

## Power Consumptions of Standalone Cisco Catalyst 3750-X and 3560-X Series Switches

Table 12 shows power consumptions of standalone Cisco Catalyst 3750-X and 3560-X Series Switches based on Alliance for Telecommunications Industry Solutions (ATIS) testing using IMIX distribution stream traffic, with input voltage of 115V AC @ 60 Hz and no PoE loading.

**Table 12.** Power Consumptions of Standalone Cisco Catalyst 3750-X and 3560-X Series

Models	Uplink Module	Power Consumption, W			
		0% Traffic	10% Traffic	100% Traffic	Weighted Average
3750X-24T & 3560X-24T	C3KX-NM-1G	93.6	92.8	93.5	93.0
3750X-24P & 3560X-24P		99.4	98.7	99.3	98.9
3750X-48T & 3560X-48T		121.3	119.7	120.4	120.0
3750X-48P & 3560X-48P		134.9	133.3	133.9	133.6
3750X-4PF & 3560X-48PF		137.4	135.8	137.2	136.2
3750X-24T & 3560X-24T	C3KX-NM-10G	95.8	95.4	98.7	95.8
3750X-24P & 3560X-24P		101.7	101.5	104.6	101.8
3750X-48T & 3560X-48T		124.2	122.7	126.0	123.3
3750X-48P & 3560X-48P		137.2	136.0	139.3	136.5
3750X-4PF & 3560X-48PF		140.9	139.6	142.9	140.1

## Safety and Compliance

Table 13 lists the safety and compliance information for the Cisco Catalyst 3750-X and 3560-X Series.

**Table 13.** Safety and Compliance Information for Cisco Catalyst 3750-X and 3560-X Series

Description	Specification
<b>Safety Certifications</b>	UL60950-1 C-UL to CAN/CSA 22.2 No.60950-1 TUV/GS to EN 60950-1 CB to IEC 60950-1 with all country deviations AS/NZS 60950-1 CE Marking NOM (through partners and distributors) GOST (Russia Safety Mark)
<b>Electromagnetic Emissions Certifications</b>	FCC Part 15 Class A EN 55022B Class A (CISPR22 Class A) VCCI Class A AS/NZS 3548 Class A or AS/NZS CISPR22 Class A KCC CE Marking GOST (Russian mark—Post FCS thru partners) CCC for PS FRU Redundant
<b>Environmental</b>	Reduction of Hazardous Substances (ROHS) 5
<b>Noise Specifications</b>	Office Product Spec: 48dBA at 30°C (refer to ISO 7779)
<b>Telco</b>	CLEI code

## Cisco Enhanced Limited Lifetime Hardware Warranty

The Cisco Catalyst 3750-X and 3560-X Series Switches come with an enhanced limited lifetime hardware warranty (E-LLW) that includes next business day delivery of replacement hardware where available and 90 days of 8x5 Cisco Technical Assistance Center (TAC) support.

Your formal warranty statement, including the warranty applicable to Cisco software, appears in the Cisco information packet that accompanies your Cisco product. We encourage you to review carefully the warranty statement shipped with your specific product before use.

Cisco reserves the right to refund the purchase price as its exclusive warranty remedy.

For further information on warranty terms, visit <http://www.cisco.com/go/warranty>. Table 14 provides information about the enhanced limited lifetime hardware warranty.

**Table 14.** Enhanced Limited Lifetime Hardware Warranty

Cisco Enhanced Limited Lifetime Hardware Warranty	
<b>Device Covered</b>	Applies to Cisco Catalyst 3750-X and 3560-X Series Switches
<b>Warranty Duration</b>	As long as the original end user continues to own or use the product, provided that fan and power supply warranty is limited to 5 years.
<b>EoL Policy</b>	In the event of discontinuance of product manufacture, Cisco warranty support is limited to 5 years from the announcement of discontinuance.
<b>Hardware Replacement</b>	Cisco or its service center will use commercially reasonable efforts to ship a replacement for next business day delivery, where available. Otherwise, a replacement will be shipped within ten (10) working days after receipt of the RMA request. Actual delivery times might vary depending on customer location.
<b>Effective Date</b>	Hardware warranty commences from the date of shipment to customer (and in case of resale by a Cisco reseller, not more than 90 days after original shipment by Cisco).
<b>TAC Support</b>	Cisco will provide during business hours, 8 hours per day, 5 days per week basic configuration, diagnosis, and troubleshooting of device-level problems for up to a 90-day period from the date of shipment of the originally purchased Cisco Catalyst 3750-X or 3560-X product. This support does not include solution or network-level support beyond the specific device under consideration.
<b>Cisco.com Access</b>	Warranty allows guest access only to Cisco.com.

### Software Policy for Cisco Catalyst 3750-X and 3560-X Series Switches

Customers with Cisco Catalyst LAN Base and IP Base software feature sets will be provided with maintenance updates and bug fixes designed to maintain the compliance of the software with published specifications, release notes, and industry standards compliance as long as the original end user continues to own or use the product or up to one year from the end-of-sale date for this product, whichever occurs earlier. Customers with licenses for our premium software images require a service support contract such as Cisco SMARTnet<sup>®</sup> Service to download updates.

This policy supersedes any previous warranty or software statement and is subject to change without notice.

### Cisco and Partner Services for Next-Generation Cisco Catalyst Fixed Switches

Enable the innovative, secure, intelligent edge in the Borderless Network Architecture using personalized services from Cisco and our partners. Through a discovery process that begins with understanding your business objectives, we help you integrate the next-generation Cisco Catalyst fixed switches into your architecture and incorporate network services onto that platform. Sharing knowledge and leading practices, we support your success every step of the way as you deploy, absorb, manage, and scale new technology. Choose from a flexible suite of support services designed to meet your business needs and help you maintain high-quality network performance while controlling operational costs. (See Table 15.)

**Table 15.** Technical Services Available for Cisco Catalyst 3750-X and 3560-X Switches

Technical Services
--------------------

**Cisco SMARTnet Service**

- Around-the-clock, global access to the Cisco Technical Assistance Center (TAC)
- Unrestricted access to the extensive Cisco.com knowledge base and tools
- Next-business-day, 8x5x4, 24x7x4, and 24x7x2 advance hardware replacement and onsite parts replacement and installation available
- Ongoing operating system software updates within the licensed feature set
- Proactive diagnostics and real-time alerts on Smart Call Home enabled devices

**Cisco Smart Foundation Service**

- Next business day advance hardware replacement as available
- Business hours access to SMB TAC (access levels vary by region)
- Access to Cisco.com SMB knowledge base
- Online technical resources through Smart Foundation Portal
- Operating system software bug fixes and patches

**Cisco SP Base Service**

- Around-the-clock, global access to the Cisco TAC
- Registered access to Cisco.com
- Next business day, 8x5x4, 24x7x4, and 24x7x2 advance hardware replacement. Return to factory option available<sup>2</sup>
- Ongoing operating system software updates<sup>1</sup>

**Cisco Focused Technical Support Services**

- 3 levels of premium, high-touch services are available:
- Cisco High-Touch Operations Management Service
- Cisco High-Touch Technical Support Service
- Cisco High-Touch Engineering Service
- Valid Cisco SMARTnet or SP Base contracts on all network equipment are required.

**Notes:**

1. Cisco operating system updates include the following: maintenance releases, minor updates, and major updates within the licensed feature set.
2. Advance hardware replacement is available in various service-level combinations. For example, 8x5xNBD indicates that shipment will be initiated during the standard 8-hour business day, 5 days a week (the generally accepted business days within the relevant region), with next business day (NBD) delivery. Where NBD is not available, same day ship is provided. Restrictions apply; for details, review the appropriate service descriptions.

**Cisco Services for Access Switching**

Cisco and our partners can help you create a robust, dependable Cisco Access Switching solution. The Cisco lifecycle approach to services defines the requisite activities at each phase of the solution lifecycle. Assessments help align your solution to business goals and gauge readiness to support new technology. Effective planning and design expedite solution adoption. Award-winning technical support increases operational efficiency and optimization improves performance, resiliency, stability, and predictability and prepares your network and teams for change. For more information, visit <http://www.cisco.com/go/services>.

**Ordering Information**

Table 16 lists ordering information for the Cisco Catalyst 3750-X and 3560-X Series. To place an order, visit the Cisco Ordering homepage at

[http://www.cisco.com/en/US/ordering/or13/or8/order\\_customer\\_help\\_how\\_to\\_order\\_listing.html](http://www.cisco.com/en/US/ordering/or13/or8/order_customer_help_how_to_order_listing.html).

**Table 16.** Cisco Catalyst 3750-X and 3560-X Series Ordering Information

Product Number	Product Description
<b>Catalyst 3750-X Series</b>	
<b>WS-C3750X-24T-L</b>	Stackable 24 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, LAN Base feature set
<b>WS-C3750X-48T-L</b>	Stackable 48 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, LAN Base feature set
<b>WS-C3750X-24P-L</b>	Stackable 24 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, LAN Base feature set
<b>WS-C3750X-48P-L</b>	Stackable 48 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, LAN Base feature set
<b>WS-C3750X-48PF-L</b>	Stackable 48 10/100/1000 Ethernet PoE+ ports, with 1100W AC power supply 1 RU, LAN Base feature set

<b>WS-C3750X-24T-S</b>	Stackable 24 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, IP Base feature set
<b>WS-C3750X-48T-S</b>	Stackable 48 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, IP Base feature set
<b>WS-C3750X-24P-S</b>	Stackable 24 10/100/1000 Ethernet PoE+ ports, with 715W AC Power Supply 1 RU, IP Base feature set
<b>WS-C3750X-48P-S</b>	Stackable 48 10/100/1000 Ethernet PoE+ ports, with 715W AC Power Supply 1 RU, IP Base feature set
<b>WS-C3750X-48PF-S</b>	Stackable 48 10/100/1000 Ethernet PoE+ ports, with 1100W AC power supply 1 RU, LAN Base feature set
<b>Catalyst 3560-X Series</b>	
<b>WS-C3560X-24T-L</b>	Standalone 24 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, LAN Base feature set
<b>WS-C3560X-48T-L</b>	Standalone 48 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, LAN Base feature set
<b>WS-C3560X-24P-L</b>	Standalone 24 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, LAN Base feature set
<b>WS-C3560X-48P-L</b>	Standalone 48 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, LAN Base feature set
<b>WS-C3560X-48P-L</b>	Standalone 48 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, LAN Base feature set
<b>WS-C3560X-48PF-L</b>	Standalone 48 10/100/1000 Ethernet PoE+ ports, with 1100W AC power supply 1 RU, LAN Base feature set
<b>WS-C3560X-24T-S</b>	Standalone 24 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, IP Base feature set
<b>WS-C3560X-48T-S</b>	Standalone 48 10/100/1000 Ethernet ports, with 350W AC power supply 1 RU, IP Base feature set
<b>WS-C3560X-24P-S</b>	Standalone 24 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, IP Base feature set
<b>WS-C3560X-48P-S</b>	Standalone 48 10/100/1000 Ethernet PoE+ ports, with 715W AC power supply 1 RU, IP Base feature set
<b>WS-C3560X-48PF-S</b>	Standalone 48 10/100/1000 Ethernet PoE+ ports, with 1100W AC power supply 1 RU, IP Base feature set
<b>Network Modules for the Catalyst 3750-X and 3560-X Series</b>	
<b>C3KX-NM-1G=</b>	1G network module spare
<b>C3KX-NM-10G=</b>	10G network module spare
<b>C3KX-NM-BLANK=</b>	Network module blank spare
<b>Power Supplies and Fan for the Catalyst 3750-X and 3560-X Series</b>	
<b>C3KX-PWR-350WAC=</b>	350W AC power supply
<b>C3KX-PWR-715WAC=</b>	715W AC power supply
<b>C3KX-PWR-1100WAC=</b>	1100W AC power supply
<b>C3KX-PWR-440WDC=</b>	440W DC power supply
<b>C3KX-PS-BLANK=</b>	Power supply blank spare
<b>C3KX-FAN-23CFM=</b>	Fan module spare
<b>eXpandable Power System (XPS) for the Catalyst 3750-X and 3560-X Series</b>	
<b>XPS-2200</b>	eXpandable Power System 2200
<b>CAB-XPS-58CM=</b>	XPS cable 58 cm spare
<b>CAB-XPS-150CM=</b>	XPS cable 150 cm spare
<b>XPS-2200-FAN=</b>	XPS 2200 fan module spare
<b>StackWise and StackPower Cables</b>	
<b>CAB-STACK-50CM=</b>	Cisco StackWise 50 cm stacking cable
<b>CAB-STACK-1M=</b>	Cisco StackWise 1 m stacking cable
<b>CAB-STACK-3M=</b>	Cisco StackWise 3 m stacking cable



<b>CAB-STACK-50CM-NH=</b>	Cisco StackWise 50 cm non-halogen lead-free stacking cable
<b>CAB-STACK-1M-NH=</b>	Cisco StackWise 1 m non-halogen lead-free stacking cable
<b>CAB-STACK-3M-NH=</b>	Cisco StackWise 3 m non-halogen lead-free stacking cable
<b>CAB-SPWR-30CM=</b>	Catalyst 3750-X StackPower cable 30 cm spare
<b>CAB-SPWR-150CM=</b>	Catalyst 3750-X StackPower cable 150 cm spare
<b>SFP+ Transceivers for Catalyst 3750-X and 3560-X Series</b>	
<b>SFP-10G-LR=</b>	10GBASE-LR SFP+ module
<b>SFP-10G-SR=</b>	10GBASE-SR SFP+ module
<b>SFP-10G-LRM=</b>	10GBASE-LRM SFP+ module
<b>SFP-H10GB-CU1M=</b>	10GBASE-CX1 SFP module
<b>SFP-H10GB-CU3M=</b>	10GBASE-CX3 SFP module
<b>SFP-H10GB-CU5M=</b>	10GBASE-CX5 SFP module
<b>SFP Transceivers for Catalyst 3750-X and 3560-X Series</b>	
<b>GLC-GE-100FX=</b>	100BASE-FX SFP on Gigabit Ethernet SFP ports
<b>GLC-LH-SM=</b>	Gigabit Ethernet SFP, LC connector LX/LH transceiver
<b>GLC-SX-MM=</b>	Gigabit Ethernet SFP, LC connector SX transceiver
<b>GLC-T=</b>	1000BASE-T SFP
<b>GLC-ZX-SM=</b>	1000BASE-ZX SFP
<b>GLC-BX-D=</b>	1000BASE-BX SFP, 1490 nm
<b>GLC-BX-U=</b>	1000BASE-BX SFP, 1310 nm
<b>CWDM-SFP-1470=</b>	Coarse wavelength-division multiplexing (CWDM) 1470 nm SFP Gigabit Ethernet and 1G/2G Fibre Channel (FC)
<b>CWDM-SFP-1490=</b>	CWDM 1490 nm SFP Gigabit Ethernet and 1G/2G FC
<b>CWDM-SFP-1510=</b>	CWDM 1510 nm SFP Gigabit Ethernet and 1G/2G FC
<b>CWDM-SFP-1530=</b>	CWDM 1530 nm SFP Gigabit Ethernet and 1G/2G FC
<b>CWDM-SFP-1550=</b>	CWDM 1550 nm SFP Gigabit Ethernet and 1G/2G FC
<b>CWDM-SFP-1570=</b>	CWDM 1570 nm SFP Gigabit Ethernet and 1G/2G FC
<b>CWDM-SFP-1590=</b>	CWDM 1590 nm SFP Gigabit Ethernet and 1G/2G FC
<b>CWDM-SFP-1610=</b>	CWDM 1610 nm SFP Gigabit Ethernet and 1G/2G FC
<b>DWDM-SFP-3033=</b>	Dense wavelength-division multiplexing (DWDM) SFP 1530.33 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3112=</b>	DWDM SFP 1531.12 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3190=</b>	DWDM SFP 1531.90 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3268=</b>	DWDM SFP 1532.68 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3425=</b>	DWDM SFP 1534.25 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3504=</b>	DWDM SFP 1535.04 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3582=</b>	DWDM SFP 1535.82 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3661=</b>	DWDM SFP 1536.61 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3819=</b>	DWDM SFP 1538.19 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3898=</b>	DWDM SFP 1538.98 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-3977=</b>	DWDM SFP 1539.77 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4056=</b>	DWDM SFP 1540.56 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4214=</b>	DWDM SFP 1542.14 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4294=</b>	DWDM SFP 1542.94 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4373=</b>	DWDM SFP 1543.73 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4453=</b>	DWDM SFP 1544.53 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4612=</b>	DWDM SFP 1546.12 nm SFP (100 GHz ITU grid)
<b>DWDM-SFP-4692=</b>	DWDM SFP 1546.92 nm SFP (100 GHz ITU grid)

DWDM-SFP-4772=	DWDM SFP 1547.72 nm SFP (100 GHz ITU grid)
DWDM-SFP-4851=	DWDM SFP 1548.51 nm SFP (100 GHz ITU grid)
DWDM-SFP-5012=	DWDM SFP 1550.12 nm SFP (100 GHz ITU grid)
DWDM-SFP-5092=	DWDM SFP 1550.92 nm SFP (100 GHz ITU grid)
DWDM-SFP-5172=	DWDM SFP 1551.72 nm SFP (100 GHz ITU grid)
DWDM-SFP-5252=	DWDM SFP 1552.52 nm SFP (100 GHz ITU grid)
DWDM-SFP-5413=	DWDM SFP 1554.13 nm SFP (100 GHz ITU grid)
DWDM-SFP-5494=	DWDM SFP 1554.94 nm SFP (100 GHz ITU grid)
DWDM-SFP-5575=	DWDM SFP 1555.75 nm SFP (100 GHz ITU grid)
DWDM-SFP-5655=	DWDM SFP 1556.55 nm SFP (100 GHz ITU grid)
DWDM-SFP-5817=	DWDM SFP 1558.17 nm SFP (100 GHz ITU grid)
DWDM-SFP-5898=	DWDM SFP 1558.98 nm SFP (100 GHz ITU grid)
DWDM-SFP-5979=	DWDM SFP 1559.79 nm SFP (100 GHz ITU grid)
DWDM-SFP-6061=	DWDM SFP 1560.61 nm SFP (100 GHz ITU grid)
<b>Catalyst 3750-X Series Product Activation Keys</b>	
C3750X-LIC=	Product activation keys for 3750-X Series
<b>3750-X LAN Base to IP Base Upgrade License</b>	
C3750X-24-L-S=	C3750X-24 LAN Base to IP Base Paper License
C3750X-48-L-S=	C3750X-48 LAN Base to IP Base Paper License
L-C3750X-24-L-S=	C3750X-24 LAN Base to IP Base E-License
L-C3750X-48-L-S=	C3750X-48 LAN Base to IP Base E-License
LL-C3750X-24-L-S=	C3750X-24 LAN Base to IP Base E-License for Used Switch
LL-C3750X-48-L-S=	C3750X-48 LAN Base to IP Base E-License for Used Switch
<b>3750-X IP Base to IP Services Upgrade</b>	
C3750X-24-IOS-S-E	C3750X-24 IP Base to IP Services factory IOS Upgrade
C3750X-48-IOS-S-E	C3750X-48 IP Base to IP Services factory IOS Upgrade
C3750X-24-S-E=	C3750X-24 IP Base to IP Services Paper License
C3750X-48-S-E=	C3750X-48 IP Base to IP Services Paper License
L-C3750X-24-S-E=	C3750X-24 IP Base to IP Services E-License
L-C3750X-48-S-E=	C3750X-48 IP Base to IP Services E-License
LL-C3750X-24-S-E=	C3750X-24 IP Base to IP Services E-License for Used Switch
LL-C3750X-48-S-E=	C3750X-48 IP Base to IP Services E-License for Used Switch
<b>3750-X LAN Base to IP Services Upgrade</b>	
C3750X-24-L-E=	C3750X-24 LAN Base to IP Services Paper License
C3750X-48-L-E=	C3750X-48 LAN Base to IP Services Paper License
L-C3750X-24-L-E=	C3750X-24 LAN Base to IP Services E-License
L-C3750X-48-L-E=	C3750X-48 LAN Base to IP Services E-License
LL-C3750X-24-L-E=	C3750X-24 LAN Base to IP Services E-License for Used Switch
LL-C3750X-48-L-E=	C3750X-48 LAN Base to IP Services E-License for Used Switch
<b>Catalyst 3560-X Series Product Activation Keys</b>	
C3560X-LIC=	Product activation keys for 3560-X Series
<b>3560-X LAN Base to IP Base Upgrade License</b>	
C3560X-24-L-S=	C3560X-24 LAN Base to IP Base Paper License
C3560X-48-L-S=	C3560X-48 LAN Base to IP Base Paper License
L-C3560X-24-L-S=	C3560X-24 LAN Base to IP Base E-License
L-C3560X-48-L-S=	C3560X-48 LAN Base to IP Base E-License

<b>LL-C3560X-24-L-S=</b>	C3560X-24 LAN Base to IP Base E-License for Used Switch
<b>LL-C3560X-48-L-S=</b>	C3560X-48 LAN Base to IP Base E-License for Used Switch
<b>3560-X IP Base to IP Services Upgrade</b>	
<b>C3560X-24-IOS-S-E</b>	C3560X-24 IP Base to IP Services factory IOS Upgrade
<b>C3560X-48-IOS-S-E</b>	C3560X-48 IP Base to IP Services factory IOS Upgrade
<b>C3560X-24-S-E=</b>	C3560X-24 IP Base to IP Services Paper License
<b>C3560X-48-S-E=</b>	C3560X-48 IP Base to IP Services Paper License
<b>L-C3560X-24-S-E=</b>	C3560X-24 IP Base to IP Services E-License
<b>L-C3560X-48-S-E=</b>	C3560X-48 IP Base to IP Services E-License
<b>LL-C3560X-24-S-E=</b>	C3560X-24 IP Base to IP Services E-License for Used Switch
<b>LL-C3560X-48-S-E=</b>	C3560X-48 IP Base to IP Services E-License for Used Switch
<b>3560-X LAN Base to IP Services Upgrade</b>	
<b>C3560X-24-L-E=</b>	C3560X-24 LAN Base to IP Services Paper License
<b>C3560X-48-L-E=</b>	C3560X-48 LAN Base to IP Services Paper License
<b>L-C3560X-24-L-E=</b>	C3560X-24 LAN Base to IP Services E-License
<b>L-C3560X-48-L-E=</b>	C3560X-48 LAN Base to IP Services E-License
<b>LL-C3560X-24-L-E=</b>	C3560X-24 LAN Base to IP Services E-License for Used Switch
<b>LL-C3560X-48-L-E=</b>	C3560X-48 LAN Base to IP Services E-License for Used Switch
<b>Spare Power Cords for the Catalyst 3750-X and 3560-X Series</b>	
<b>CAB-3KX-AC=</b>	AC Power Cord for Catalyst 3K-X (North America)
<b>CAB-3KX-AC-AP=</b>	AC Power Cord for Catalyst 3K-X (Australia)
<b>CAB-3KX-AC-AR=</b>	AC Power Cord for Catalyst 3K-X (Argentina)
<b>CAB-3KX-AC-SW=</b>	AC Power Cord for Catalyst 3K-X (Switzerland)
<b>CAB-3KX-AC-UK=</b>	AC Power Cord for Catalyst 3K-X (United Kingdom)
<b>CAB-3KX-AC-JP=</b>	AC Power Cord for Catalyst 3K-X (Japan)
<b>CAB-3KX-AC-EU=</b>	AC Power Cord for Catalyst 3K-X (Europe)
<b>CAB-3KX-AC-IT=</b>	AC Power Cord for Catalyst 3K-X (Italy)
<b>CAB-3KX-AC-IN=</b>	AC Power Cord for Catalyst 3K-X (India)
<b>CAB-3KX-AC-CN=</b>	AC Power Cord for Catalyst 3K-X (China)
<b>CAB-3KX-AC-DN=</b>	AC Power Cord for Catalyst 3K-X (Denmark)
<b>CAB-3KX-AC-IS=</b>	AC Power Cord for Catalyst 3K-X (Israel)
<b>Spare Accessory and Rack Mount Kits for the Catalyst 3750-X and 3560-X Series</b>	
<b>C3KX-ACC-KIT=</b>	Accessory kit for Catalyst 3750-X and 3560-X Series
<b>C3KX-RACK-KIT=</b>	Rack mount kit for Catalyst 3750-X and 3560-X Series



**Americas Headquarters**  
 Cisco Systems, Inc.  
 San Jose, CA

**Asia Pacific Headquarters**  
 Cisco Systems (USA) Pte. Ltd.  
 Singapore

**Europe Headquarters**  
 Cisco Systems International BV  
 Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

CCDE, CCENT, CCSI, Cisco Eos, Cisco Explorer, Cisco HealthPresence, Cisco IronPort, the Cisco logo, Cisco Nurse Connect, Cisco Pulse, Cisco SensorBase, Cisco StackPower, Cisco StadiumVision, Cisco TelePresence, Cisco TrustSec, Cisco Unified Computing System, Cisco WebEx, DCE, Flip Channels, Flip for Good, Flip Mino, Flipshare (Design), Flip Ultra, Flip Video, Flip Video (Design), Instant Broadband, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn, Cisco Capital, Cisco Capital (Design), Cisco:Financed (Stylized), Cisco Store, Flip Gift Card, and One Million Acts of Green are service marks; and Access Registrar, Aironet, AllTouch, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Lumin, Cisco Nexus, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, Continuum, EtherFast, EtherSwitch, Event Center, Explorer, Follow Me Browsing, GainMaker, iLYNX, IOS, iPhone, IronPort, the IronPort logo, Laser Link, LightStream, Linksys, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, PCNow, PIX, PowerKEY, PowerPanels, PowerTV, PowerTV (Design), PowerVu, Prisma, ProConnect, ROSA, SenderBase, SMARTnet, Spectrum Expert, StackWise, WebEx, and the WebEx logo are registered trademarks of Cisco and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1002R)